

PWM MOTOR DRIVING DEVICE

BACKGROUND OF THE INVENTION

Field of the Invention

5 The present invention relates to a PWM (pulse-width modulation) motor driving device for driving a brushless DC (direct-current) motor, such as a capstan motor employed in a VCR (videocassette recorder), while controlling the rotation rate thereof by a PWM-based method.

Description of the Prior Art

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
220

Here, in a PWM motor driving device, those transistors are, instead of one or both of them being kept ON, switched between ON and OFF at a predetermined frequency (hereinafter this will be called PWM switching). Thus, on the basis of the ON/OFF duty factor achieved by such PWM switching, the amount of electric power supplied to the motor, and thus the rotation rate thereof, is controlled.

In a device that drives a motor linearly, to prevent the upper output transistors from being saturated, the base currents thereof are controlled according to the highest among the U-phase voltage (the voltage at the node PU), the V-phase voltage (the voltage at the node PV), and the W-phase voltage (the voltage at the node PW); similarly, to prevent the lower output transistors from being saturated, the base currents thereof are controlled according to the lowest among the U-phase voltage, the V-phase voltage, and the W-phase voltage.

Here, for example, when the upper output transistor T_{UU} turns from ON to OFF, the back electromotive force appearing in the coil L_U causes, as indicated by an arrow Y_2 in Fig. 15, a current to flow through a diode D parasitic on the lower output transistor T_{UL} , and thereby causes the U-phase voltage to become lower than the ground level by the voltage drop across the diode D. As a result, whereas ideally the lowest voltage should appear in, among the U-, V-, and W-phases, the phase of whichever coil is currently being driven by the lower output transistors, actually a voltage lower than that appears in the phases of the other coils that are currently not being driven by the lower output transistors.

For this reason, in a PWM motor driving device, while the upper output transistors are undergoing PWM switching, if prevention of saturation of the output transistors is attempted by the method described above, the controlling of the base

currents of the lower output transistors is attempted according to the voltage of the phase of the coil that is currently being driven by the upper output transistors, and therefore the lower output transistors cannot be properly prevented from saturation. Similarly, when the lower output transistors are undergoing PWM switching, the upper output transistors cannot be properly prevented from saturation.

Moreover, in a driving method based on PWM, since the coils of the motor are driven with pulses as described above, whereas good motor rotation efficiency can be achieved, smooth motor rotation cannot be obtained because the waveform of the currents obtained to be passed through the coils of the motor is not sinusoidal.

SUMMARY OF THE INVENTION

An object of the present invention is to provide a PWM motor driving device that achieves enhanced motor rotation characteristics by preventing saturation of output transistors.

Another object of the present invention is to provide a PWM motor driving device that produces less ripples in motor rotation.

To achieve the above objects, according to one aspect of the present invention, a PWM motor driving device that controls the amount of electric power supplied to a motor by controlling the ON/OFF duty factor of an output transistor connected between a power source and the motor is provided with: phase detecting means for detecting, among a plurality of phases of the motor, the phase which is currently being driven by the output transistor; and saturation preventing means for performing control according to the voltage of the phase detected by the

phase detecting means in such a way that the output transistor is not saturated.

This circuit configuration permits the output transistors to be controlled so as not to be saturated according to the voltage of the phase in which the motor is currently being driven. Thus, for example, when the upper output transistors are
5 undergoing PWM switching, the lower output transistors are controlled so as not to be saturated no longer according to the voltage of the phase in which the motor is currently being driven by the upper output transistors as practiced conventionally. This helps obtain better motor rotation characteristics.

According to another aspect of the present invention, a PWM motor driving
10 device that controls the amount of electric power supplied to a motor by controlling the ON/OFF duty factor of a switching device connected between a power source and the motor is provided with: ripple cancel signal generating means for generating, based on a signal representing the rotational position of the motor, a
15 ripple cancel signal having a triangular waveform with maxima thereof synchronized with minima in torque; and duty factor controlling means for controlling the ON/OFF duty factor of the switching device according to a signal obtained by adding the torque control signal and the ripple cancel signal together.

This circuit configuration permits the ON/OFF duty factor, achieved by PWM switching, of the output transistors to be controlled according to a signal
20 having a triangular waveform with maxima thereof synchronized with minima in torque. This makes it possible to pass more current at times of low torque and thereby achieve smoother motor rotation.

BRIEF DESCRIPTION OF THE DRAWINGS

This and other objects and features of the present invention will become clear from the following description, taken in conjunction with the preferred embodiments with reference to the accompanying drawings in which:

5 Fig. 1 is a block diagram of a PWM motor driving device embodying the invention;

Fig. 2 is a diagram showing the internal circuit configuration of the three-phase synthesizing circuit shown in Fig. 1;

Fig. 3 is a timing chart of the signals observed at relevant points in Fig. 2;

Fig. 4 is a circuit diagram of the ternary differential circuit shown in Fig. 2;

Fig. 5 is a circuit diagram of the upper saturation prevention circuit;

Fig. 6 is a circuit diagram of the lower saturation prevention circuit;

Fig. 7 is a circuit diagram of the lower phase detection circuit;

Fig. 8 is a block diagram of another PWM motor driving device embodying the invention;

Fig. 9 is a circuit diagram of the upper phase detection circuit;

Fig. 10 is a block diagram of still another PWM motor driving device embodying the invention;

Fig. 11 is a diagram showing the internal circuit configuration of the three-phase synthesizing circuit shown in Fig. 10;

20 Fig. 12 is a timing chart of the signals observed at relevant points in Fig. 11;

Fig. 13 is a circuit diagram of the ternary differential circuit shown in Fig. 11;

Fig. 14 is a circuit diagram of a ripple cancel circuit; and

Fig. 15 is a circuit diagram of the output stage of a motor driving device.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Hereinafter, embodiments of the present invention will be described with reference to the drawings. Fig. 1 shows a block diagram of a PWM motor driving device embodying the invention. Hole devices HU, HV, and HW attached around the rotor, i.e. rotating portion, of a motor output hole signals H1, H2, and H3, respectively, which are then amplified by a hole amplifier 1 to become signals A1, A2, and A3 and are then fed to a three-phase synthesizing circuit 2. These three hole signals H1, H2, and H3 indicate the rotational position of the motor.

10 A control amplifier 4 receives, at its inverting input terminal (-), a reference voltage V_{REF} and, at its non-inverting input terminal (+), a torque control signal T_{CTL} , which is a voltage signal. The control amplifier 4 outputs a current I_{CTL} that varies according to the voltage difference between the voltages it receives at its inverting and non-inverting input terminals (-) and (+). Specifically, as the voltage of the torque control signal T_{CTL} becomes higher relative to the reference voltage V_{REF} , the current I_{CTL} output from the control amplifier 4 increases. A current supply circuit 5 supplies a current that increases and decreases with the current I_{CTL} output from the control amplifier 4 to a resistor 6, an upper saturation prevention circuit 9, and a lower saturation prevention circuit 10.

20 The torque control signal T_{CTL} is a signal output from a circuit (not shown) that detects the rotation rate of the motor and compares the detected rotation rate with the specified rotation rate. The voltage of the torque control signal T_{CTL} becomes higher as the actual rotation rate of the motor becomes lower relative to the specified rotation rate, and the former becomes lower as the latter becomes

higher. Thus, the current I_{CTL} output from the control amplifier 4 is a signal that varies according to the error of the actual rotation rate of the motor relative to the specified rotation rate.

The current output from the current supply circuit 5 is converted by the resistor 6 into a voltage, which is fed to the non-inverting input terminal (+) of a PWM comparator 7. To its inverting input terminal (-), a high-frequency triangular wave output from a triangular wave generating circuit 8 is fed.

As a result, the PWM comparator 7 outputs a high-frequency binary signal (hereinafter called the PWM signal) S_{PWM} . The duty factor of the high-level period of this PWM signal S_{PWM} relative to one period thereof becomes greater as the voltage of the torque control signal T_{CTL} becomes higher, and the former becomes smaller as the latter becomes lower. The PWM signal S_{PWM} is fed to the three-phase synthesizing circuit.

An output amplifier 3 is composed of NPN-type power transistors T_{UU} , T_{VU} , T_{WU} , T_{UL} , T_{VL} , and T_{WL} . The upper output transistors T_{UU} , T_{VU} , and T_{WU} receive at their collectors a motor drive voltage V_M , and the lower output transistors T_{UL} , T_{VL} , and T_{WL} have their emitters connected to ground GND. The emitter of the upper output transistor T_{UU} and the collector of the lower output transistor T_{UL} are connected to the U-phase coil L_U of the motor, the emitter of the upper output transistor T_{VU} and the collector of the lower output transistor T_{VL} are connected to the V-phase coil L_V of the motor, and the emitter of the upper output transistor T_{WU} and the collector of the lower output transistor T_{WL} are connected to the W-phase coil of the motor. The output transistors T_{UU} , T_{VU} , T_{WU} , T_{UL} , T_{VL} , and T_{WL} receive, at their bases, currents UU , VU , WU , UL , VL , and WL , respectively, output from the

three-phase synthesizing circuit 2.

As shown in Fig. 3, the hole signals H1, H2, and H3, which are output from the hole devices HU, HV, and HW, respectively, and which are sinusoidal waves displaced in phase by 120° relative to one another, are individually advanced in phase by 30° and then amplified by the hole amplifier 1 to become signals A1, A2, and A3.

Fig. 2 shows the internal circuit configuration of the three-phase synthesizing circuit 2. As shown in Fig. 3, a logarithmic conversion circuit 21 extracts the positive portions of the signals A1, A2, and A3 to produce switching signals B1, B2, and B3, respectively, and extracts the negative portions of the signals A1, A2, and A3 to produce switching signals B4, B5, and B6, respectively.

Fig. 4 shows the internal circuit configuration of the ternary differential circuit 22. PNP-type transistors 2201 and 2202 constitute a current mirror circuit. Through the input-side transistor 2201 flows, as its collector current, a current I_{UO} output from the upper saturation prevention circuit 9, described later. On the other hand, the output-side transistor 2202 has its collector connected to the collector of an NPN-type transistor 2203.

The NPN-type transistor 2203, together with an NPN-type transistor 2204, constitutes a current mirror circuit. As described above, to the collector of the transistor 2203, the collector of the transistor 2202 is connected. To the collector of the transistor 2204, the emitters of NPN-type transistors 2205, 2206, and 2207 are connected.

NPN-type transistors 2208 and 2209 constitute a current mirror circuit. Through the input-side transistor 2208 flows, as its collector current, a current I_{LO}

output from the lower saturation prevention circuit 10, described later. On the other hand, the output-side transistor 2209 has its collector connected to the collector of an PNP-type transistor 2210.

5 The PNP-type transistor 2210, together with a PNP-type transistor 2211, constitutes a current mirror circuit. As described above, the transistor 2210 has its collector connected to the collector of the transistor 2209. The output-side transistor 2211 has its collector connected to the emitters of PNP-type transistors 2212, 2213, and 2214.

10 The transistor 2205 receives at its base the switching signal B1, the transistor 2206 receives at its base the switching signal B2, the transistor 2207 receives at its base the switching signal B3, the transistor 2212 receives at its base the switching signal B4, the transistor 2213 receives at its base the switching signal B5, and the transistor 2214 receives at its base the switching signal B6.

15 Through the transistors 2205, 2212, 2206, 2213, 2207, and 2214 flow, as their collector currents, currents I1, I2, I3, I4, I5, and I6 output from the ternary differential circuit 22. The currents I1, I2, I3, I4, I5, and I6 output from the ternary differential circuit 22 are amplified by the preamplifier 23 to become currents UU, UL, VU, VL, WU, and WL, respectively, and are then fed to the bases of the output transistors T_{UU} , T_{UL} , T_{VU} , T_{VL} , T_{WU} , and T_{WL} of the output amplifier 3.

20 Of the currents output from the ternary differential circuit 22, the currents I1, I3, and I5 related to the currents fed to the bases of the upper output transistors T_{UU} , T_{VU} , and T_{WU} are fed to the preamplifier 23 through switches 24, 25, and 26, respectively. These switches 24, 25, and 26 are kept ON when the PWM signal S_{PWM} is at a high level and are kept OFF when the PWM signal S_{PWM} is at a low level.

Accordingly, the upper output transistors of the output amplifier 3 are switched between ON and OFF by PWM switching at the same frequency and by the same duty factor as the PWM signal S_{PWM} .

The circuit configuration described above permits appropriate switching of the coil to be driven according to the rotational position of the motor, and thereby makes the motor rotate. As the duty factor of the high-level period of the PWM signal S_{PWM} relative to one period thereof becomes greater, the length of time for which the upper output transistors of the output amplifier 3 are kept ON by PWM switching becomes longer, and thus the amount of electric power supplied to the coil (in other words, the current with which the coils are driven) becomes larger, and thus, provided that the load on the motor is constant, the rotation rate of the motor becomes higher.

Moreover, as the current I_{UO} output from the upper saturation prevention circuit 9 increases, the currents that flow into the bases of the upper output transistors increase; on the other hand, as the current I_{LO} output from the lower saturation prevention circuit 10 increases, the currents that flow into the bases of the lower output transistors increase.

Fig. 5 shows the internal circuit configuration of the upper saturation prevention circuit 9. NPN-type transistors 901 and 902 constitute a current mirror circuit. The transistors 901 and 902 have their emitters grounded through resistors 903 and 904, respectively. The input-side transistor 901 receives at its collector the current I_{CTL} output from the current supply circuit 5. The output-side transistor 902 has its collector connected to the collector of a diode-connected PNP-type transistor 905.

5 The transistor 905 has its emitter connected to the motor drive voltage V_M through two resistors 909 and 910 connected in series. From the node between the two resistors 909 and 910, a constant current I_{CC1} flows out. PNP-type transistors 906, 907, and 908 have their bases connected together to the base of the transistor 905.

10 The emitter of the transistor 906 is connected through a resistor 911 to the node PU between the emitter of the upper output transistor T_{UU} and the collector of the lower output transistor T_{UL} within the output amplifier 3, the emitter of the transistor 907 is connected through a resistor 912 to the node PV between the emitter of the upper output transistor T_{VU} and the collector of the lower output transistor T_{VL} within the output amplifier 3, and emitter of the transistor 908 is connected through a resistor 913 to the node PW between the emitter of the upper output transistor T_{WU} and the collector of the lower output transistor T_{WL} within the output amplifier 3.

15 NPN-type transistors 914 and 915 constitute a current mirror circuit, with the transistor 914 placed on the input side and the transistor 915 placed on the output side. The transistor 914 has its emitter grounded through a resistor 916, and, to its collector, the collectors of the transistors 906, 907, and 908 are connected together. The transistor 915 has its emitter grounded through a resistor 917, and has its collector connected to the collector of an NPN-type transistor 918.

20 The NPN-type transistor 918, together with an NPN-type transistor 919, constitutes a current mirror circuit, with the transistor 918 placed on the input side and the transistor 919 placed on the output side. The transistors 918 and 919 have their emitters grounded through resistors 920 and 921, respectively. To the

collector of the transistor 918, a constant current output from a constant-current source 922 is fed through a resistor 923. The current I_{UO} that flows through the transistor 919 as its collector current is used as the output of the upper saturation prevention circuit 9. To the node between the constant-current source 922 and the resistor 923, a capacitor (not shown) is connected externally for phase compensation.

Configured as described above, the upper saturation prevention circuit 9 operates as follows. As the U-phase voltage (the voltage at the node PU), the V-phase voltage (the voltage at the node PV), and the W-phase voltage (the voltage at the node PW) become higher relative to the emitter voltage of the transistor 905, the output current I_{UO} decreases. As described previously, as the output current I_{UO} decreases, the base currents of the upper output transistors T_{UU} , T_{VU} , and T_{WU} of the output amplifier 3 decrease, and thus the U-phase, V-phase, and W-phase voltages become lower.

Thus, feedback control is exercised on the base currents of the upper output transistors of the output amplifier 3 in such a way that the highest among the U-phase, V-phase, and W-phase voltages is limited below a specified upper limit voltage (the emitter voltage of the transistor 905). In this way, saturation of the upper output transistors T_{UU} , T_{VU} , and T_{WU} is prevented.

Here, let the resistances of the resistors 909 and 910 be $R1$ and $R2$, respectively, then the emitter voltage V_E of the transistor 905 is given by

$$V_E = V_M - I_{CC1} \cdot R1 - I_{CTL}' \cdot (R1 + R2)$$

which means that it varies according to the output current I_{CTL}' of the current supply circuit 5. Thus, the saturation prevention level of the upper output transistors (the upper limit of the U-phase, V-phase, and W-phase voltages) is controlled according to the torque control signal T_{CTL} . This enhances controllability of the rotation rate of the motor.

Fig. 6 shows the internal circuit configuration of the lower saturation prevention circuit 10. PNP-type transistors 1001 and 1002 have their emitters connected together to a constant-current source 1003. The transistor 1001 has its base connected to the emitter of a PNP-type transistor 1004. The transistor 1004 has its base grounded through a resistor 1005. To the node between the transistor 1004 and the resistor 1005, a constant current I_{CC2} output from a constant-current circuit 1006 and the current I_{CTL}' output from the current supply circuit 5 flow in.

The transistor 1002 has its base connected to the emitters of PNP-type transistors 1007, 1008, and 1009. The transistors 1002, 1007, 1008, and 1009 have their collectors grounded. The transistors 1007, 1008, and 1009 receive at their bases three voltages V_{UL} , V_{VL} , and V_{WL} output from a lower phase detection circuit 11, described later, through resistors 1010, 1011, and 1012, respectively.

The transistor 1001 has its collector connected to the collector of an NPN-type transistor 1013. The NPN-type transistor 1013, together with an NPN-type transistor 1014, constitutes a current mirror circuit, with the transistor 1013 placed on the input side and the transistor 1014 placed on the output side. The transistors 1013 and 1014 have their emitters grounded through resistors 1015 and 1016, respectively.

PNP-type transistors 1017, 1018, and 1019 constitute a current mirror circuit.

The input-side transistor 1017 and the output-side transistor 1018 have their emitters connected to the supplied voltage V_{CC} through resistors 1020 and 1021, respectively. The input-side transistor 1017 has its collector connected to the collector of the transistor 1014 through a resistor 1022. The current I_{LO} that flows
5 through the transistor 1018 as its collector current is used as the output of the lower saturation prevention circuit 10. To the node between the collector of the transistor 1014 and the resistor 1022, a capacitor (not shown) is connected externally for phase compensation.

Configured as described above, the lower saturation prevention circuit 10 operates as follows. As the three voltages V_{UL} , V_{VL} , and V_{WL} output from the lower phase detection circuit 11 become lower relative to the base voltage of the transistor 1004, the output current I_{LO} decreases. As described previously, as the output current I_{LO} decreases, the base currents of the lower output transistors T_{UL} , T_{VL} , and T_{WL} of the output amplifier 3 decrease, and thus the U-phase, V-phase, and W-phase voltages become higher.
10
15

Thus, feedback control is exercised on the base currents of the lower output transistors of the output amplifier 3 in such a way that the lowest among the three voltages V_{UL} , V_{VL} , and V_{WL} output from the lower phase detection circuit 11 is limited above a specified lower limit voltage (the base voltage of the transistor
20 1004).

Here, let the resistance of the resistor 1005 be R , then the base voltage V_B of the transistor 1004 is given by

$$V_B = (I_{CTL}' + I_{CC2}) \cdot R$$

which means that it varies according to the output current I_{CTL}' of the current supply circuit 5. Thus, the saturation prevention level of the lower output transistors (the lower limit of the U-phase, V-phase, and W-phase voltages) is controlled according to the torque control signal T_{CTL} . This enhances controllability of the rotation rate of the motor.

The lower phase detection circuit 11, as shown in Fig. 7, which shows its internal circuit configuration, is composed of a first circuit 111, a second circuit 112, and a third circuit 113. The first circuit 111 is configured as follows. An NPN-type transistor 1101 has its base grounded through a resistor 1102, has its emitter grounded, and has its collector connected to the motor drive voltage V_M through two resistors 1103 and 1104 connected in series. To the node between the base of the transistor 1101 and the resistor 1102, a signal corresponding to the switching signal B4 produced by the three-phase synthesizing circuit 2 is fed. A PNP-type transistor 1105 has its base connected to the node between the resistors 1103 and 1104, has its emitter connected to the motor drive voltage V_M , and has its collector connected to the node PU within the output amplifier 3 through a resistor 1106.

The second and third circuits 112 and 113 have the same circuit configuration as the first circuit 111, and therefore their description will be omitted. The only differences with the second and third circuits 112 and 113, respectively, are that the signals fed to the node between the base of the transistor 1101 and the resistor 1102 are signals corresponding to the switching signals B5 and B6 produced by the three-phase synthesizing circuit 2, and that the destinations to

which the collector of the transistor 1105 is connected through the resistor 1106 are the nodes PV and PW within the output amplifier 3. The three voltages V_{UL} , V_{VL} , and V_{WL} appearing at the node between the transistor 1105 and the resistor 1106 in the first, second, and third circuits 111, 112, and 113, respectively, are used as the 5 outputs of the lower phase detection circuit 11.

Configured as described above, the lower phase detection circuit 11 operates as follows. In the first circuit 111, when the switching signal B4 is at a low level, the transistor 1101 is OFF, and thus the transistor 1105 is OFF, with the result that the first circuit 111 outputs the U-phase voltage; on the other hand, when the 10 switching signal B4 is at a high level, the transistor 1101 is ON, and thus the transistor 1105 is ON, with the result that the first circuit 111 outputs a voltage approximately equal to the motor drive voltage V_M .

Likewise, the second circuit 112, when the switching signal B5 is at a low level, outputs the V-phase voltage, and, when the switching signal B5 is at a high level, outputs a voltage approximately equal to the motor drive voltage V_M . Likewise, the third circuit 113, when the switching signal B6 is at a low level, outputs the W-phase voltage, and, when the switching signal B6 is at a high level, outputs a voltage approximately equal to the motor drive voltage V_M .

In summary, the voltage output from the lower phase detection circuit 11 as 20 the voltage of the phase of whichever coil is currently being driven by the lower output transistors always has a value lower than the voltages of the other phases. This is because, when any of the switching signals B4, B5, and B6 is at a low level, the lower output transistor T_{UL} , T_{VL} , or T_{WL} , respectively, drives the U-phase, V-phase, or W-phase coil L_U , L_V , or L_W , respectively.

In this way, by the operation of the lower saturation prevention circuit 10 and the lower phase detection circuit 11, the voltage of the phase of whichever coil is currently being driven by the lower output transistors of the output amplifier 3 is kept above the specified lower limit voltage (specifically, the base voltage of the transistor 1004), and thus saturation of the lower output transistors T_{UL} , T_{VL} , and T_{WL} is prevented.

As described above, in this embodiment, the base currents of the lower output transistors are controlled so as not to saturate those transistors on the basis of the voltage of the phase of whichever coil is currently being driven by the lower output transistors of the output amplifier 3. Thus, even though the upper output transistors of the output amplifier 3 are switched between ON and OFF by PWM switching, the base currents of the lower output transistors are controlled so as not to saturate those transistors no longer on the basis of the voltage of the phase of whichever coil is currently being driven by the upper output transistors as practiced conventionally. This enhances motor rotation characteristics.

In a case where the lower output transistors of the output amplifier 3 are switched between ON and OFF by PWM switching, as shown in Fig. 8, the circuit configuration is so modified that the signals output from an upper phase detection circuit 12 are fed to the upper saturation prevention circuit 9. In this case, the lower saturation prevention circuit 10 receives, instead of the three voltages V_{UL} , V_{VL} , and V_{WL} output from the lower phase detection circuit 11, the U-phase, V-phase, and W-phase voltages, respectively.

Fig. 9 shows the internal circuit configuration of the upper phase detection circuit 12. The upper phase detection circuit 12 is composed of a first circuit 121,

a second circuit 122, and a third circuit 123. The first circuit 121 is configured as follows. A PNP-type transistor 1201 has its base connected to the motor drive voltage V_M through a resistor 1202, has its emitter connected to the motor drive voltage V_M , and has its collector grounded through two resistors 1203 and 1204
5 connected in series.

To the node between the base of the transistor 1201 and the resistor 1202, a signal corresponding to the switching signal B1 produced by the three-phase synthesizing circuit 2 is fed. An NPN-type transistor 1205 has its base connected to the node between the resistors 1203 and 1204, has its emitter grounded, and has
10 its collector connected to the node PU within the output amplifier 3 through a resistor 1206.

The second and third circuits 122 and 123 have the same circuit configuration as the first circuit 121, and therefore their description will be omitted. The only differences with the second and third circuits 122 and 123, respectively, are that the signals fed to the node between the base of the transistor 1201 and the resistor 1202 are signals corresponding to the switching signals B2 and B3 produced by the three-phase synthesizing circuit 2, and that the destinations to which the collector of the transistor 1205 is connected through the resistor 1206 are the nodes PV and PW within the output amplifier 3. The three voltages V_{UU} , V_{VU} ,
15 and V_{WU} appearing at the node between the transistor 1205 and the resistor 1206 in the first, second, and third circuits 121, 122, and 123, respectively, are fed to the upper saturation prevention circuit 9.
20

Configured as described above, the upper phase detection circuit 12 operates as follows. In the first circuit 121, when the switching signal B1 is at a high level,

the transistor 1201 is OFF, and thus the transistor 1205 is OFF, with the result that the first circuit 121 outputs the U-phase voltage; on the other hand, when the switching signal B1 is at a low level, the transistor 1201 is ON, and thus the transistor 1205 is ON, with the result that the first circuit 121 outputs a voltage
5 approximately equal to the ground level.

Likewise, the second circuit 122, when the switching signal B2 is at a high level, outputs the V-phase voltage, and, when the switching signal B2 is at a low level, outputs a voltage approximately equal to the ground level. Likewise, the third circuit 123, when the switching signal B3 is at a high level, outputs the W-
10 phase voltage, and, when the switching signal B3 is at a low level, outputs a voltage approximately equal to the ground level.

In summary, the voltage output from the upper phase detection circuit 12 as the voltage of the phase of whichever coil is currently being driven by the upper output transistors always has a value higher than the voltages of the other phases.
15 This is because, when any of the switching signals B1, B2, and B3 is at a high level, the upper output transistor T_{UU} , T_{VU} , or T_{WU} , respectively, drives the U-phase, V-phase, or W-phase coil L_U , L_V , or L_W , respectively.

In this way, by feeding the outputs of the upper phase detection circuit 12 to the upper saturation prevention circuit 9, the base currents of the upper output
20 transistors are controlled so as not to saturate those transistors on the basis of the voltage of the phase of whichever coil is currently being driven by the upper output transistors of the output amplifier 3. This enhances motor rotation characteristics.

In a case where both the upper and lower output transistors of the output amplifier 3 are switched between ON and OFF by PWM switching, the circuit

configuration is so modified as to include both the lower phase detection circuit 11 and the upper phase detection circuit 12.

Fig. 10 shows a block diagram of still another PWM motor driving device embodying the invention. In this figure, such circuit elements as are found also in Fig. 1, which is a block diagram of the previously described embodiment, are identified with the same reference numerals, and their descriptions will be omitted.

The hole signals A1, A2, and A3 output from the hole amplifier 1 are fed to a three-phase synthesizing circuit 14. The lower output transistors T_{UL} , T_{VL} , and T_{WL} of the output amplifier 3 have their emitters connected to ground GND through a resistor R. A current supply circuit 15 feeds a ripple cancel circuit 13 and a resistor 16 with a current that increases and decreases with the current I_{CTL} output from the control amplifier 4.

The current I_{CTL} output from the control amplifier 4 and the current I_{CAN} output from the ripple cancel circuit 13 are added together, and the sum current is converted by the resistor 16 into a voltage, which is fed to the non-inverting input terminal (+) of a current feedback amplifier 17. On the other hand, to its inverting input terminal (-), the voltage across the resistor R, and thus a voltage that varies according to the current with which the motor is driven, is fed.

The current feedback amplifier 17 outputs a current I_{FS} that varies according to the voltage difference between the voltages fed to its non-inverting and inverting input terminals (+) and (-). Specifically, as the sum current of the current I_{CTL} output from the control amplifier 4 and the current I_{CAN} output from the ripple cancel circuit 13 increases, and as the motor drive current decreases, the current I_{FS} output from the current feedback amplifier 17 increases.

The current I_{FS} output from the current feedback amplifier 17 is converted by a resistor 18 into a voltage, which is fed to the non-inverting input terminal (+) of the PWM comparator 7. On the other hand, to its inverting input terminal (-), a high-frequency triangular wave output from the triangular wave generating circuit 8 is fed.

As a result, the duty factor of the high-level period of the PWM signal S_{PWM} , which is a high-frequency binary signal output from the PWM comparator 7, relative to one period thereof is controlled according to, as well as the torque control signal T_{CTL} and the motor drive current, the current I_{CAN} output from the ripple cancel circuit 13. Specifically, as the voltage of the torque control signal T_{CTL} becomes higher, as the current I_{CAN} output from the ripple cancel circuit 13 increases, and as the motor drive current decreases, the duty factor of the high-level period of the PWM signal S_{PWM} relative to one period thereof becomes greater.

Fig. 11 shows the internal circuit configuration of the three-phase synthesizing circuit 14. This three-phase synthesizing circuit 14 has the same configuration as the three-phase synthesizing circuit 2 shown in Fig. 2 of the previously described embodiment except that the former has a logarithmic conversion circuit 27 and a ternary differential circuit 28 in place of the logarithmic conversion circuit 21 and the ternary differential circuit 22 of the latter, and therefore descriptions will be given only of the logarithmic conversion circuit 27 and the ternary differential circuit 28.

As shown in Fig. 12, the logarithmic conversion circuit 27 extracts the positive portions of the signals A1, A2, and A3 to produce switching signals B1, B2, and B3, respectively, and extracts the negative portions of the signals A1, A2, and

A3 to produce switching signals B4, B5, and B6, respectively. In addition, the logarithmic conversion circuit 27 produces absolute value signals Z1, Z2, and Z3 by taking the absolute values of the signals A1, A2, and A3, respectively. These absolute value signals Z1, Z2, and Z3 are fed to the ripple cancel circuit 13.

5 The ternary differential circuit 28, as shown in Fig. 13, which shows its internal circuit configuration, differs from the ternary differential circuit 22 shown in Fig. 4 of the previously described embodiment in that the current that flows through the transistor 2201 as its collector current is a constant current that flows into a constant-current circuit 2215 having one end grounded, and that the current that flows through the transistor 2208 as its collector current is a constant current that flows out of a constant-current source having one end connected to the power source.

10
11
12
13
14
15
16
17
18
19
20

Fig. 14 shows the internal circuit configuration of the ripple cancel circuit 13. NPN-type transistors 1301 and 1302 constitute a current mirror circuit. The transistors 1301 and 1302 have their emitters grounded through resistors 1303 and 1304, respectively. The input-side transistor 1301 receives at its collector the output current $I_{CTL'}$ of the current supply circuit 15. The output-side transistor 1302 has its collector connected to the collector of a PNP-type transistor 1305. Although not illustrated, a terminal is provided at the node between the emitter of the transistor 1302 and the resistor 1304 so that a resistor can be connected thereto to adjust the ripple cancel factor.

The PNP-type transistor 1305, together with a PNP-type transistor 1306, constitutes a current mirror circuit. The transistors 1305 and 1306 have their emitters connected to the supplied voltage V_{CC} through resistors 1319 and 1320,

respectively. As described above, the collector of the input-side transistor 1305 is connected to the collector of the transistor 1302. To the collector of the output-side transistor 1306, the emitters of PNP-type transistors 1307, 1308, 1309, and 1310 are connected together.

5 The transistors 1308, 1309, and 1310 receive at their bases the absolute value signals Z1, Z2, and Z3, respectively, produced by the three-phase synthesizing circuit 2. Moreover, the transistors 1308, 1309, and 1310 have their bases connected to one end of resistors 1312, 1313, and 1314, respectively, which have their other end connected together. The transistor 1307 has its base connected to the node common to the resistors 1312, 1313, and 1314 through a resistor 1311. The node common to the resistors 1311, 1312, 1313, and 1314 is biased.

10 NPN-type transistors 1315 and 1316 constitute a current mirror circuit. The transistors 1315 and 1316 have their emitters grounded through resistors 1317 and 1318, respectively. To the collector of the input-side transistor 1315, the collectors of the transistors 1308, 1309, and 1010 are connected together. To the collector of the output-side transistor 1316, the collector of the transistor 1307 is connected. Thus, the ripple cancel circuit 13 outputs the difference current I_{CAN} between the collector currents of the transistors 1307 and 1316, and this current
15
20 I_{CAN} is fed to the resistor 16.

Configured as described above, the ripple cancel circuit 13 operates in such a way that, the current I_{CAN} output therefrom has a waveform, as shown in the timing chart of Fig. 12, similar to the waveform traced by the minimum values among the absolute value signals Z1, Z2, and Z3 produced by the three-phase

synthesizing circuit 2. Thus, the current I_{CAN} output from the ripple cancel circuit 13 is a signal having a triangular waveform with maxima thereof synchronized with the moments at which any of the hole signal H1, H2, and H3 has zero amplitude, i.e. the moments at which torque hits its minima.

5 Accordingly, the lower the torque in a given rotational position, the longer the length of time for which the upper output transistors are kept ON. This helps cancel shortage of torque wherever torque is low and thereby achieve smoother motor rotation. This is because, as the current I_{CAN} output from the ripple cancel circuit 13 increases, the duty factor of the high-level period of the PWM signal S_{PWM} relative to one period thereof becomes greater.

10 Moreover, in this embodiment, the level of the current I_{CAN} output from the ripple cancel circuit 13 varies according to the torque control signal T_{CTL} , and this enhances the controllability of the rotation rate of the motor.

15 In a case where the upper output transistors are switched between ON and OFF by PWM switching, it is preferable that, as in the embodiment described above, the resistor R for detecting the motor drive current be connected on the ground GND side. The reason is as follows. As shown in Fig. 15, for example, when the upper output transistor T_{UU} is switched between ON and OFF by PWM switching, even after the upper output transistor T_{UU} has turned from ON to OFF, the back
20 electromotive force appearing in the coil L_U causes a current to flow through a diode D parasitic on the lower output transistor T_{UL} as indicated by an arrow Y_2 . If the resistor R is connected on the motor drive voltage V_M side, this current cannot be detected.

For a similar reason, in a case where the lower output transistors are

switched between ON and OFF by PWM switching, it is preferable that the resistor for detecting the motor drive current be connected on the motor drive voltage side, because doing so makes more accurate detection of the motor drive current possible and thereby enhances controllability.

5 In the embodiment described above, the motor drive current is fed back. This, however, is not always necessary. In a case where the motor drive current is not fed back, the sum current of the output current I_{CTL} of the control amplifier 4 and the output current I_{CAN} of the ripple cancel circuit 13 is converted by the resistor 16 into a voltage, and this voltage is fed to the non-inverting input terminal
10 (+) of the PWM comparator 7. Higher controllability is obtained, however, when the motor drive current is fed back.